

Update for SH-400/500/810HD

1. Download the TP list (according to your region , select the suitable TP list, such as if you locate in European countries, then select TP-European file. Do the same for Asian and American) under:
www.sat-hero.com
2. Open the Excel file
3. Save file and use “.CSV” as suffixal name.
4. Copy the “.CSV” file to U-disk
5. Turn on the SH-400/500/810HD satellite finder, and insert U disk.
6. Select “USB” under main menu.
7. Enter USB menu, select submenu: Upgrade by USB
8. Upgrade mode select: CSV
9. Locate Cursor to: Update from file..., and enter U disk.
10. Select the “.CSV” file in the U disk, then press “OK” button to enter.
11. Wait the finder to be upgrade automatically and restart.
12. Finish satellite parameters upgrade.

Note: after upgrade, the former parameters and programs list will be deleted.